



This article *does not* meet Forum Nokia Wiki quality standards or the information included may not be complete.
Please help *improve* this article by adding links and further information.

Contents

- [1 Setting Item Lis 8](#)
- [2 Setting Item Lis 7](#)
- [3 Setting Item Lis 6](#)
- [4 Setting Item Lis 1](#)

Setting Item Lis 8

This happens if you create a Binary Switch Item from a resource file. The values for the `AVKON_ENUMERATED_TEXT` resources **MUST** be *one*(1) and *zero* (0).

Setting Item Lis 7

Got it when used `CAknBinaryPopupSettingItem` instead of `CAknEnumeratedTextPopupSettingItem` in `CreateSettingItemL(...)`.

Setting Item Lis 6

This is the most common of these. It **will** happen if you create an enumerated text setting item and you set its input as a value that is not in the list. If you create the selection values dynamically, this will happen always if your input value is not zero.

Setting Item Lis 1

This Panic is related to creating a **Text Setting Item** in a Dynamic Setting List. It occurs if you forget to set empty item text i.e. if you forget to call `SetEmptyItemTextL` for `CAknTextSettingItem`.

This panic actually appears while editing the text setting item; when all the characters are erased and its text becomes empty.

See [Create Dynamic Settings Pages](#) for more information about enumerated setting items. --[TK2000](#) 17:43, 22 January 2009 (EET)