



| | | | |
|-----------------|------------------------------|----------------------|-----------------------|
| ID | TSS000644 | Creation date | May 10, 2007 |
| Platform | S60 2nd Edition, FP2 and FP3 | Devices | |
| Category | Symbian C++ | Subcategory | Networking, Telephony |

Keywords (APIs, classes, methods, functions):

Overview

Retrieving current network information on S60 2nd Edition, Feature Pack 2 devices

Description

CTelephony API is supported only from S60 2nd Edition, Feature Pack 3 onwards. Even though the API (etel3rdparty.h) is present in the S60 2nd Edition, Feature Pack 2 SDK, it is not supported by S60 2nd Edition, FP2 devices (Nokia 6630, Nokia 6680).

Solution

Symbian provides a Mobinfo 3rd Party Telephony Library for devices based on Symbian OS v7.0, v7.0s, v8.0a, and v8.1a. With Mobinfo, 3rd parties can get information about

- * IMEI, IMSI, and own phone numbers
- * Network availability and change notification
- * Network and location identification
- * Battery and signal strength notification

Mobinfo is provided as a public, redistributable library. It can be downloaded from <https://developer.symbian.com/wiki/display/pub/Symbian+OS+system+libraries>

To make use of the API, you need to utilize two headers (mobileinfo.h, mobinfotypes.h) and a single library, mobinfo.dll.

Mobinfo API itself consists of three main classes

- CMobileInfo
- CMobileNetworkInfo
- CMobileContext

Asynchronous methods from Mobinfo should always be used via active objects (the client must derive from CActive).

For example, retrieving current network information:

```
CMobileNetworkInfo::GetCurrentNetwork( TMobileNetwork& aMobNetInfo, TRequestStatus& aStatus );
```

TSS000644_-_Retrieving_current_network_information_on_S60_2nd_Edition,_Feature_Pack_2_devices

GetCurrentNetwork returns information about the network the handset is currently registered on. aStatus will be completed with KErrAccessDenied when in flight mode.